NOCAP[™], Pop-Free, 3 V_{RMS} Audio Line Driver with Adjustable Gain

The NCS2632 is a pop-free stereo line driver. It uses ON Semiconductor's patented NOCAP technology which allows the elimination of the external DC-blocking capacitors by providing ground-referenced outputs through the generation of an internal negative supply rail. The device can drive $3 V_{RMS}$ into a 600 load at 5 V power supply. By eliminating the two external heavy coupling capacitors, the NOCAP approach offers significant space and cost savings compared to similar audio solutions.

The NCS2632 has differential inputs and is available with an external adjustable gain ranging from ± 1 V/V to ± 10 V/V. The gain is adjusted with external resistors. The device can also be configured as a 2nd order low pass filter to complement DAC's and SOC converters. In addition to the NOCAP architecture, it contains specific circuitry to prevent "Pop & Click" noise from occurring during Enable / Shutdown transitions. The Signal-to-Noise Ratio reaches 105 dB, offering high fidelity audio sound. The NCS2632 exhibits a high power supply rejection with a typical value of 90 dB. This device also features an Under–Voltage Protection (UVP) function which can be adjusted using an external resistor bridge. The device is available in a TSSOP–14 package.

Features

- NOCAP
 - Eliminates Pop/Clicks
 - ٠



PIN FUNCTION AND DESCRIPTION

Pin Name

ELECTRICAL CHARACTERISTICS, $T_A = 25^{\circ}C$ (unless otherwise noted)

Parameter	Symbol	Test Conditions	Min	Тур	Max	Unit
Output Offset Voltage	V _{OS}	$V_{DD} = 2.5 V$ to 5 V, Voltage follower – gain = 1		100	400	V
High-Level Input Current (EN)	I _{IH}	$VDD = 5 V, VI = V_{DD}$			100	nA
Low-Level Input Current (EN)	I _{IL}	VDD = 5 V, VI = 0 V			100	nA
Supply Current						-

Supply Current

TYPICAL CHARACTERISTICS



Figure 11. Crosstalk vs. Frequency, RL = 2.5 k\Omega, V_{DD} = 3.3 V, V_O

APPLICATION INFORMATION

DESCRIPTION

The NCS2632 is a stereo line driver with a NOCAP architecture. This architecture eliminates the need to use two large, external capacitors required by conventional audio line driver applications. The NCS2632 is basically composed of two true ground amplifiers with internal power supply rail, one UVP-circuit block, and short-circuit protection. The gain of the NCS2632 can be adjusted with two external resistors.

The NOCAP approach is a patented architecture that requires only two 1 F low ESR ceramic capacitors (fly capacitor and reservoir capacitor). It generates a symmetrical positive and negative voltage and it allows the output of the amplifiers to be biased around the ground (True Ground).

The NCS2632 includes a special circuitry for eliminating any pop and click noise during turn on and turn off time. This circuitry combined with the true ground output architecture and a trimmed output offset voltage makes the elimination of pop and click particularly efficient.

UNDER-VOLTAGE PROTECTION (UVP) PIN MANAGEMENT

The UVP pin can be used to shut down the audio line driver by monitoring the board's main power supply. Then the line driver can be shut down before upstream devices disable, contributing this way to eliminate potential source of pop noise.

The device shuts down when the UVP voltage goes below 1.25 V typically. To monitor the lower main power supply limit, an external voltage divider constituted with three resistors, RUP, RDW and RHYS is used (Figure 21). Resistors values have to be chosen based on the requested power supply shutdown threshold and hysteresis for a given application. It is recommended to have RHYS >> RDW // RUP. RHYS is optional in the case where hysteresis is not necessary.





GAIN SETTING RESISTOR SELECTION (RIN and RFB)

 R_{IN} and R_{FB} set the closed–loop gain of the amplifier. The resistor values have to be chosen so that amplifier stability is preserved. A low gain configuration (close to 1) minimizes the THD + noise values and maximizes the signal to noise ratio.

 R_{FB} $Vin - H R_{IN}$ $Vin + H R_{FB}$

A closed–loop gain in the range of 1 to 10 is recommended to optimize overall system performance.

Selecting values that are too low requires a relatively large input ac-coupling capacitor, $C_{\rm IN}$. Selecting values that are too high increases the overall noise of the amplifier.

$$Av = \frac{Vout}{Vin+ - Vin-} = \frac{R_{FB}}{R_{in}} \qquad (eq. 9)$$





 $Av = \frac{Vout}{Vin-} = \frac{-R_{FB}}{R_{IN}} \qquad (eq. 10)$

Figure 23. Inverting Gain Configuration



$$Av = \frac{V_{out}}{Vin+} = 1 + \frac{R_{FB}}{R_{IN}} \text{ (eq. 11)}$$

Figure 24. Non–Inverting Gain Configuration

onsemi, , and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or incruit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi